

Programmable Switching D.C. Power Supply (Multi-Range D.C. Power Supply)



PSW-Series



FEATURES

- * Voltage Rating : 30V/80V/160V/250V/800V, Output Power Rating : 360W-1080W
- * Constant Power Output for Multi-Range (V & I) Operation
- * C.V / C.C Priority ; Particularly Suitable for the Battery and LED Industry
- * Adjustable Slew Rate
- * Series Operation(2 units in Series)for(30V/80V/160V), Parallel Operation(3 units in Parallel) for (30V/80V/160V/250V/800V)
- * High Efficiency and High Power Density
- * 1/2, 1/3, 1/6 Rack Mount Size Design (EIA/JIS Standard) for 360W, 720W, 1080W
- * Standard Interface : LAN, USB, Analog Control Interface
- * Optional Interface : GPIB-USB Adaptor, RS232-USB Cable
- * LabVIEW Driver



PSW 80-40.5 (0-80V, 0-40.5A, 1080W)



PSW 160-7.2 (0-160V, 0-7.2A, 360W)



PSW 80-13.5 (0-80V, 0-13.5A, 360W)

The PSW-Series is a single-output multi-range programmable switching DC Power Supply covering a power range up to 1080W. This series of products include fifteen models with the combination of 30V, 80V, 160V, 250V and 800V rated voltages and 360W, 720W and 1080W maximum output powers. The multi-range feature allows the flexible and efficient configuration of voltage and current within the rated power range. As the PSW-Series can be connected in series for maximum 2 units or in parallel for maximum 3 units, the capability of connecting multiple PSW-Series units for higher voltage or higher current output provides a broad coverage of applications. With the flexibility of multi-range power utilization and series/parallel connection, the PSW-Series significantly reduces the users' cost for various power supply products to accommodate the projects with different power requirements.

The C.V/C.C priority selection of the PSW-Series is a very useful feature for DUT protection. The conventional power supply normally operates under C.V mode when the power output is turned on. This could bring a high inrush current to the capacitive load or current-intensive load at the power output-on stage. Taking the I-V curve verification of LED as an example, it becomes a very challenging task to perform this measurement using a conventional power supply. With LED connected to a power supply under C.V mode as the initial setting, when the power output is turned on and the voltage rises to the LED forward voltage, the current will suddenly peak up and exceed the preset value of current limit. Upon detecting this high current, the power supply starts the transition from C.V mode to C.C mode. Though the current becomes stable after the C.C mode being activated, the current spike occurred at the C.V and C.C crossover point may possibly damage the DUT. At the power output-on stage, the PSW-Series is able to operate under C.C priority to limit the current spike occurred at the threshold voltage and therefore protects DUT from the inrush current damage.

The adjustable slew rate of the PSW-Series allows users to set for either output voltage or output current, a specific rise time from low to high level transition, and a specific fall time from high to low level transition. This facilitates the characteristic verification of a DUT during voltage or current level changes with controllable slew rates. Most manufacturing tests of lighting device or large capacitor during power output-on are associated with the occurrence of high surge current, which can greatly reduce the life time of the DUT. To prevent inrush current from damaging current-intensive devices, a smooth and slow voltage transition during power On-Off can significantly reduce the spike current and protect the device from high current damage.

The OVP and OCP are provided with the PSW-Series. Both OVP and OCP levels can be selected, with default level set at 110%, of the rated voltage/current of the power supply. When any of the protection levels is tripped, the power output will be switched off to protect the DUT. The PSW-Series provides USB Host/Device and LAN interfaces as standard, GPIB-USB adapter and RS232-USB cable as optional. The LabView driver and the Data Logging PC software are supported on all the available interfaces. An analog control/monitoring connector is also available on the rear panel for external control of power On/Off and external monitoring of power output Voltage and Current.

PARALLEL OPERATION (3 UNITS)

| MODEL | SINGLE UNIT | 2 UNITS | 3 UNITS |
|--------------|-------------|------------|-------------|
| PSW 30-36 | 30V/36A | 30V/72A | 30V/108A |
| PSW 30-72 | 30V/72A | 30V/144A | 30V/216A |
| PSW 30-108 | 30V/108A | 30V/216A | 30V/324A |
| PSW 80-13.5 | 80V/13.5A | 80V/27A | 80V/40.5A |
| PSW 80-27 | 80V/27A | 80V/54A | 80V/81A |
| PSW 80-40.5 | 80V/40.5A | 80V/81A | 80V/121.5A |
| PSW 160-7.2 | 160V/7.2A | 160V/14.4A | 160V/21.6A |
| PSW 160-14.4 | 160V/14.4A | 160V/28.8A | 160V/43.2A |
| PSW 160-21.6 | 160V/21.6A | 160V/43.2A | 160V/64.8A |
| PSW 250-4.5 | 250V/4.5A | 250V/9A | 250V/13.5A |
| PSW 250-9 | 250V/9A | 250V/18A | 250V/27A |
| PSW 250-13.5 | 250V/13.5A | 250V/27A | 250V/40.5A |
| PSW 800-1.44 | 800V/1.44A | 800V/2.88A | 800V/4.32A |
| PSW 800-2.88 | 800V/2.88A | 800V/5.76A | 800V/8.64A |
| PSW 800-4.32 | 800V/4.32A | 800V/8.64A | 800V/12.96A |

SERIES OPERATION (2 UNITS)

| MODEL | SINGLE UNIT | 2 UNITS |
|--------------|-------------|------------|
| PSW 30-36 | 30V/36A | 60V/36A |
| PSW 30-72 | 30V/72A | 60V/72A |
| PSW 30-108 | 30V/108A | 60V/108A |
| PSW 80-13.5 | 80V/13.5A | 160V/13.5A |
| PSW 80-27 | 80V/27A | 160V/27A |
| PSW 80-40.5 | 80V/40.5A | 160V/40.5A |
| PSW 160-7.2 | 160V/7.2A | 320V/7.2A |
| PSW 160-14.4 | 160V/14.4A | 320V/14.4A |
| PSW 160-21.6 | 160V/21.6A | 320V/21.6A |
| PSW 250-4.5 | N/A | N/A |
| PSW 250-9 | N/A | N/A |
| PSW 250-13.5 | N/A | N/A |
| PSW 800-1.44 | N/A | N/A |
| PSW 800-2.88 | N/A | N/A |
| PSW 800-4.32 | N/A | N/A |

| SPECIFICATIONS | | | | | | | | | |
|---|---|--|---|--------------------------------------|---|---|--------------------------------------|---|---|
| | PSW 30-36 | PSW 30-72 | PSW 30-108 | PSW 80-13.5 | PSW 80-27 | PSW 80-40.5 | PSW 160-7.2 | PSW 160-14.4 | PSW 160-21.6 |
| OUTPUT RATING | | | | | | | | | |
| Voltage | 0 ~ 30V | 0 ~ 30V | 0 ~ 30V | 0 ~ 80V | 0 ~ 80V | 0 ~ 80V | 0 ~ 160V | 0 ~ 160V | 0 ~ 160V |
| Current | 0 ~ 36A | 0 ~ 72A | 0 ~ 108A | 0 ~ 13.5A | 0 ~ 27A | 0 ~ 40.5A | 0 ~ 7.2A | 0 ~ 14.4A | 0 ~ 21.6A |
| Power | 360W | 720W | 1080W | 360W | 720W | 1080W | 360W | 720W | 1080W |
| REGULATION(CV) | | | | | | | | | |
| Load Line | 20mV | 20mV | 20mV | 45mV | 45mV | 45mV | 85mV | 85mV | 85mV |
| | 18mV | 18mV | 18mV | 43mV | 43mV | 43mV | 83mV | 83mV | 83mV |
| REGULATION(CC) | | | | | | | | | |
| Load Line | 41mA | 77mA | 113mA | 18.5mA | 32mA | 45.5mA | 12.2mA | 19.4mA | 26.6mA |
| | 41mA | 77mA | 113mA | 18.5mA | 32mA | 45.5mA | 12.2mA | 19.4mA | 26.6mA |
| RIPPLE & NOISE (Noise Bandwidth 20MHz; Ripple Bandwidth=1MHz) | | | | | | | | | |
| CV p-p | 60mV | 80mV | 100mV | 60mV | 80mV | 100mV | 60mV | 80mV | 100mV |
| CV rms | 7mV | 11mV | 14mV | 7mV | 11mV | 14mV | 7mV | 11mV | 20mV |
| CC rms | 72mA | 144mA | 216mA | 27mA | 54mA | 81mA | 15mA | 30mA | 45mA |
| PROGRAMMING ACCURACY | | | | | | | | | |
| Voltage | 0.1% +10mV | 0.1% +10mV | 0.1% +10mV | 0.1% +10mV | 0.1% +10mV | 0.1% +10mV | 0.1% +100mV | 0.1% +100mV | 0.1% +100mV |
| Current | 0.1% +30mA | 0.1% +60mA | 0.1% +100mA | 0.1% +10mA | 0.1% +30mA | 0.1% +40mA | 0.1% +5mA | 0.1% +15mA | 0.1% +20mA |
| MEASUREMENT ACCURACY | | | | | | | | | |
| Voltage | 0.1% +10mV | 0.1% +10mV | 0.1% +10mV | 0.1% +10mV | 0.1% +10mV | 0.1% +10mV | 0.1% +100mV | 0.1% +100mV | 0.1% +100mV |
| Current | 0.1% +30mA | 0.1% +60mA | 0.1% +100mA | 0.1% +10mA | 0.1% +30mA | 0.1% +40mA | 0.1% +5mA | 0.1% +15mA | 0.1% +20mA |
| RESPONSE TIME | | | | | | | | | |
| Raise Time | 50ms | 50ms | 50ms | 50ms | 50ms | 50ms | 100ms | 100ms | 100ms |
| Fall Time(Full Load) | 50ms | 50ms | 50ms | 50ms | 50ms | 50ms | 100ms | 100ms | 100ms |
| Fall Time(No Load) | 500ms | 500ms | 500ms | 500ms | 500ms | 500ms | 1000ms | 1000ms | 1000ms |
| Load Transient Recover Time (Load change from 50-100%) | 1ms | 1ms | 1ms | 1ms | 1ms | 1ms | 2ms | 2ms | 2ms |
| PROGRAMMING RESOLUTION (By PC Remote Control Mode) | | | | | | | | | |
| Voltage | 1mV | 1mV | 1mV | 2mV | 2mV | 2mV | 3mV | 3mV | 3mV |
| Current | 1mA | 2mA | 3mA | 1mA | 2mA | 3mA | 1mA | 2mA | 3mA |
| MEASUREMENT RESOLUTION (By PC Remote Control Mode) | | | | | | | | | |
| Voltage | 1mV | 1mV | 1mV | 2mV | 2mV | 2mV | 3mV | 3mV | 3mV |
| Current | 1mA | 2mA | 3mA | 1mA | 2mA | 3mA | 1mA | 2mA | 3mA |
| SERIES AND PARALLEL CAPABILITY | | | | | | | | | |
| Parallel Operation | Up to 3 units including the master unit | | | | | | | | |
| Series Operation | Up to 2 units including the master unit | | | | | | | | |
| PROTECTION FUNCTION | | | | | | | | | |
| OVP | 3 ~ 33V | 3 ~ 33V | 3 ~ 33V | 8 ~ 88V | 8 ~ 88V | 8 ~ 88V | 16 ~ 176V | 16 ~ 176V | 16 ~ 176V |
| OCP | 3.6 ~ 39.6A | 5 ~ 79.2A | 5 ~ 118.8A | 1.35 ~ 14.85A | 2.7 ~ 29.7A | 4.05 ~ 44.55A | 0.72 ~ 7.92A | 1.44 ~ 15.84A | 2.16 ~ 23.76A |
| OHP | Activated by elevated internal temperatures | | | | | | | | |
| FRONT PANEL DISPLAY ACCURACY, 4 digits | | | | | | | | | |
| Voltage | 0.1%±20mV | 0.1%±20mV | 0.1%±20mV | 0.1%±20mV | 0.1%±20mV | 0.1%±20mV | 0.1%±100mV | 0.1%±100mV | 0.1%±100mV |
| Current | 0.1%±40mA | 0.1%±70mA | 0.1%±100mA | 0.1%±20mA | 0.1%±40mA | 0.1%±50mA | 0.1%±5mA | 0.1%±30mA | 0.1%±30mA |
| ENVIRONMENT CONDITION | | | | | | | | | |
| Operation Temp | 0°C ~ 50°C | | | | | | | | |
| Storage Temp | -25°C ~ 70°C | | | | | | | | |
| Operating Humidity | 20% ~ 85% RH; No condensation | | | | | | | | |
| Storage Humidity | 90% RH or Less; No condensation | | | | | | | | |
| READ BACK TEMP COEFFICIENT | | | | | | | | | |
| Voltage | 100ppm/°C of rated output voltage : after a 30 minute warm-up | | | | | | | | |
| Current | 200ppm/°C of rated output current : after a 30 minute warm-up | | | | | | | | |
| OTHER | | | | | | | | | |
| Analog Control Interface | Yes | | | | | | | | |
| Fan | With thermal sensing control | | | | | | | | |
| POWER SOURCE | 85VAC-265VAC, 47-63Hz, single phase | | | | | | | | |
| DIMENSIONS & WEIGHT | | | | | | | | | |
| | 71(W)x124(H)x350(D) mm ; Approx. 3kg | 142(W)x124(H)x350(D)mm ; Approx. 5.3kg | 214(W)x124(H)x350(D) mm ; Approx. 7.5kg | 71(W)x124(H)x350(D) mm ; Approx. 3kg | 142(W)x124(H)x350(D) mm ; Approx. 5.3kg | 214(W)x124(H)x350(D) mm ; Approx. 7.5kg | 71(W)x124(H)x350(D) mm ; Approx. 3kg | 142(W)x124(H)x350(D) mm ; Approx. 5.3kg | 214(W)x124(H)x350(D) mm ; Approx. 7.5kg |

Programmable Switching D.C. Power Supply (Multi-Range D.C. Power Supply)

| SPECIFICATIONS | | | | | | |
|--|---|---|---|--|---|---|
| | PSW 250-4.5 | PSW 250-9 | PSW 250-13.5 | PSW 800-1.44 | PSW 800-2.88 | PSW 800-4.32 |
| OUTPUT RATING | | | | | | |
| Voltage | 0 ~ 250V | 0 ~ 250V | 0 ~ 250V | 0 ~ 800V | 0 ~ 800V | 0 ~ 800V |
| Current | 0 ~ 4.5A | 0 ~ 9A | 0 ~ 13.5A | 0 ~ 1.44A | 0 ~ 2.88A | 0 ~ 4.32A |
| Power | 360W | 720W | 1080W | 360W | 720W | 1080W |
| REGULATION(CV) | | | | | | |
| Load Line | 130mV 128mV | 130mV 128mV | 130mV 128mV | 405mV 403mV | 405mV 403mV | 405mV 403mV |
| REGULATION(CC) | | | | | | |
| Load Line | 9.5mA 9.5mA | 14mA 14mA | 18.5mA 18.5mA | 6.44mA 6.44mA | 7.88mA 7.88mA | 9.32mA 9.32mA |
| RIPPLE & NOISE (Noise Bandwidth 20MHz; Ripple Bandwidth=1MHz) | | | | | | |
| CV p-p | 80mV | 100mV | 120mV | 150mV | 200mV | 200mV |
| CV rms | 15mV | 15mV | 15mV | 30mV | 30mV | 30mV |
| CC rms | 10mA | 20mA | 30mA | 5mA | 10mA | 15mA |
| PROGRAMMING ACCURACY | | | | | | |
| Voltage | 0.1%+200mV | 0.1%+200mV | 0.1%+200mV | 0.1%+400mV | 0.1%+400mV | 0.1%+400mV |
| Current | 0.1%+5mA | 0.1%+10mA | 0.1%+15mA | 0.1%+2mA | 0.1%+4mA | 0.1%+6mA |
| MEASUREMENT ACCURACY | | | | | | |
| Voltage | 0.1%+200mV | 0.1%+200mV | 0.1%+200mV | 0.1%+400mV | 0.1%+400mV | 0.1%+400mV |
| Current | 0.1%+5mA | 0.1%+10mA | 0.1%+15mA | 0.1%+2mA | 0.1%+4mA | 0.1%+6mA |
| RESPONSE TIME | | | | | | |
| Raise Time | 100ms | 100ms | 100ms | 150ms | 150ms | 150ms |
| Fall Time(Full Load) | 150ms | 150ms | 150ms | 300ms | 300ms | 300ms |
| Fall Time(No Load) | 1200ms | 1200ms | 1200ms | 2000ms | 2000ms | 2000ms |
| Load Transient | 2ms | 2ms | 2ms | 2ms | 2ms | 2ms |
| Recover Time (Load change from 50~100%) | | | | | | |
| PROGRAMMING RESOLUTION (By PC Remote Control Mode) | | | | | | |
| Voltage | 5mV | 5mV | 5mV | 14mV | 14mV | 14mV |
| Current | 1mA | 1mA | 1mA | 1mA | 1mA | 1mA |
| MEASUREMENT RESOLUTION (By PC Remote Control Mode) | | | | | | |
| Voltage | 5mV | 5mV | 5mV | 14mV | 14mV | 14mV |
| Current | 1mA | 1mA | 1mA | 1mA | 1mA | 1mA |
| SERIES AND PARALLEL CAPABILITY | | | | | | |
| Parallel Operation | 3 | 3 | 3 | 3 | 3 | 3 |
| Series Operation | N/A | N/A | N/A | N/A | N/A | N/A |
| PROTECTION FUNCTION | | | | | | |
| OVP | 20 ~ 275V | 20 ~ 275V | 20 ~ 275V | 20 ~ 880V | 20 ~ 880V | 20 ~ 880V |
| OC | 0.45 ~ 4.95A | 0.9 ~ 9.9A | 1.35 ~ 14.85A | 0.144 ~ 1.584A | 0.288 ~ 3.168A | 0.432 ~ 4.752 |
| OHP | Activated by elevated internal temperatures | | | | | |
| FRONT PANEL DISPLAY ACCURACY (4 digits) | | | | | | |
| Voltage | 0.1%±200mV | 0.1%±200mV | 0.1%±200mV | 0.1%±400mV | 0.1%±400mV | 0.1%±400mV |
| Current | 0.1%±5mA | 0.1%±10mA | 0.1%±20mA | 0.1%±2mA | 0.1%±4mA | 0.1%±6mA |
| ENVIRONMENT CONDITION | | | | | | |
| Operation Temp | 00 ~ 50 °C | | | | | |
| Storage Temp | -25 ~ 70 °C | | | | | |
| Operating Humidity | 20% ~ 85% RH; No condensation | | | | | |
| Storage Humidity | 90% RH or Less; No condensation | | | | | |
| READ BACK TEMP COEFFICIENT | | | | | | |
| Voltage | 100ppm/°C of rated output voltage : after a 30 minute warm-up | | | | | |
| Current | 200ppm/°C of rated output current : after a 30 minute warm-up | | | | | |
| OTHER | | | | | | |
| Analog Control Interface | Yes USB/LAN/GPIB (Option) | | | | | |
| Fan | With thermal sensing control | | | | | |
| POWER SOURCE | 85VAC~265VAC, 47~63Hz, single phase | | | | | |
| DIMENSIONS & WEIGHT | | | | | | |
| | 71 (W)x124 (H) x350 (D) mm ; Approx. 3kg | 142 (W)x124 (H) x350 (D) mm ; Approx. 5.3kg | 214 (W)x124 (H) x350 (D) mm ; Approx. 7.5kg | 71 (W)x124 (H) x350 (D) mm ; Approx. 3kg | 142 (W)x124 (H) x350 (D) mm ; Approx. 5.3kg | 214 (W)x124 (H) x350 (D) mm ; Approx. 7.5kg |



PSW-Series

PSW-Series (LV) Rear Panel



PSW-Series (HV) Rear Panel



ORDERING INFORMATION

| | |
|--------------|--|
| PSW 30-36 | (0-30V/0-36A/360W) Multi-Range DC Power Supply |
| PSW 30-72 | (0-30V/0-72A/720W) Multi-Range DC Power Supply |
| PSW 30-108 | (0-30V/0-108A/1080W) Multi-Range DC Power Supply |
| PSW 80-13.5 | (0-80V/0-13.5A/360W) Multi-Range DC Power Supply |
| PSW 80-27 | (0-80V/0-27A/720W) Multi-Range DC Power Supply |
| PSW 80-40.5 | (0-80V/0-40.5A/1080W) Multi-Range DC Power Supply |
| PSW 160-7.2 | (0-160V/0-7.2A/360W) Multi-Range DC Power Supply |
| PSW 160-14.4 | (0-160V/0-14.4A/720W) Multi-Range DC Power Supply |
| PSW 160-21.6 | (0-160V/0-21.6A/1080W) Multi-Range DC Power Supply |
| PSW 250-4.5 | (0-250V/0-4.5A/360W) Multi-Range DC Power Supply |
| PSW 250-9 | (0-250V/0-9A/720W) Multi-Range DC Power Supply |
| PSW 250-13.5 | (0-250V/0-13.5A/1080W) Multi-Range DC Power Supply |
| PSW 800-1.44 | (0-800V/0-1.44A/360W) Multi-Range DC Power Supply |
| PSW 800-2.88 | (0-800V/0-2.88A/720W) Multi-Range DC Power Supply |
| PSW 800-4.32 | (0-800V/0-4.32A/1080W) Multi-Range DC Power Supply |

ACCESSORIES

CD-ROM x 1 (Programming Manual, User Manual),
 GTL-123 Test Lead x 1 (for PSW 30V/80V/160V),
 Power Cord x 1 (Region dependent), GTL-240 USB Cable " L " Type x 1,
 PSW-004 Basic Accessories Kit x 1 (for PSW 30V/80V/160V),
 Includes : M4 Terminal screws and washers x 2, Air Filter x 1,
 Analog control protection dummy x 1, Analog control lock lever x 1,
 M8 terminal bolts, nuts and washers x 2,
 PSW-008 Basic Accessories kit for PSW 250V/800V models
 PSW-009 Output terminal cover for 30V/80V/160V models
 PSW-011 Output terminal cover for 250V/800V models
 PSW-012 High voltage output terminal for 250V/800V model

OPTIONAL ACCESSORIES

| | |
|-----------|--|
| PSW-001 | Accessory Kit |
| PSW-002 | Simple IDC Tool |
| PSW-003 | Contact Removal Tool |
| PSW-005 | Cable for 2 Units of PSW-Series in Series Mode Connection (for PSW 30V/80V/160V) |
| PSW-006 | Cable for 2 Units of PSW-Series in Parallel Mode Connection |
| PSW-007 | Cable for 3 Units of PSW-Series in Parallel Mode Connection |
| GUG-001 | GPIB to USB Adaptor |
| GRA-410-J | Rack Mount Kit (JIS) |
| GRA-410-E | Rack Mount Kit (EIA) |
| GET-001 | Extended Terminal (for PSW 30V/80V/160V) |
| GET-002 | Extended Terminal (for PSW 250V/800V) |
| GTL-130 | Test lead : 2 x red, 2 x black (for PSW 250V/800V) |
| PSW-010 | Large filter (Type II/III) |
| GTL-248 | GPIB Cable, Double Shielded, 2000mm |
| GTL-250 | GPIB Cable, Double Shielded, 600mm |
| GTL-251 | USB-GPIB Adapter, GPIB-USB-HS, USB 2.0, Hi-Speed USB compliance, 2000mm |
| GUR-001 | USB to RS-232 Cable, 300mm |

GUR-001 USB to RS-232 Cable

For: PSW-Series, 300mm

